



Flange Type	WR-90
Pass-band #1	9.93 ÷ 10.18 GHz (2.5% FBW)
Pass-band #2	10.4 ÷ 10.65 GHz (2.4% FBW)
Insertion Loss	0.35dB @ centre frequency
Return Loss	>22dB
Channel isolation	65dB
Dimensions (W x L x H)	130 x 130 x 15 mm